ECE276A: Sensing & Estimation in Robotics Lecture 11: Extended and Unscented Kalman Filtering

Instructor:

Nikolay Atanasov: natanasov@ucsd.edu

Teaching Assistants: Mo Shan: moshan@eng.ucsd.edu Arash Asgharivaskasi: aasghari@eng.ucsd.edu

UC San Diego

Electrical and Computer Engineering

Bayes Filter



• **Prior**:
$$p_{t|t}(\mathbf{x}_t) := p(\mathbf{x}_t \mid \mathbf{z}_{0:t}, \mathbf{u}_{0:t-1})$$

• Prediction: $p_{t+1|t}(\mathbf{x}) = \int p_f(\mathbf{x} \mid \mathbf{s}, \mathbf{u}_t) p_{t|t}(\mathbf{s}) d\mathbf{s}$

► Update:
$$p_{t+1|t+1}(\mathbf{x}) = \frac{p_h(\mathbf{z}_{t+1}|\mathbf{x})p_{t+1|t}(\mathbf{x})}{p(\mathbf{z}_{t+1}|\mathbf{z}_{0:t},\mathbf{u}_{0:t})} = \frac{p_h(\mathbf{z}_{t+1}|\mathbf{x})p_{t+1|t}(\mathbf{x})}{\int p_h(\mathbf{z}_{t+1}|\mathbf{s})p_{t+1|t}(\mathbf{s})d\mathbf{s}}$$

Kalman Filter

• A Bayes filter with the following **assumptions**:

- The prior pdf $p_{t|t}$ is Gaussian
- The motion model is linear in the state \mathbf{x}_t with Gaussian noise \mathbf{w}_t
- The observation model is linear in the state \mathbf{x}_t with Gaussian noise \mathbf{v}_t
- The motion noise w_t and observation noise v_t are independent of each other, of the state x_t, and across time

$$\blacktriangleright \text{ Prior: } \mathbf{x}_t \mid \mathbf{z}_{0:t}, \mathbf{u}_{0:t-1} \sim \mathcal{N}(\boldsymbol{\mu}_{t|t}, \boldsymbol{\Sigma}_{t|t})$$

Motion Model:

$$\begin{aligned} \mathbf{x}_{t+1} &= f(\mathbf{x}_t, \mathbf{u}_t, \mathbf{w}_t) := F\mathbf{x}_t + G\mathbf{u}_t + \mathbf{w}_t, \quad \mathbf{w}_t \sim \mathcal{N}(0, W) \\ \mathbf{x}_{t+1} \mid \mathbf{x}_t, \mathbf{u}_t \sim \mathcal{N}(F\mathbf{x}_t + G\mathbf{u}_t, W), \quad F \in \mathbb{R}^{d_x \times d_x}, G \in \mathbb{R}^{d_x \times d_u}, \ W \in \mathbb{R}^{d_x \times d_x} \end{aligned}$$

Observation Model:

$$\begin{split} & \mathbf{z}_t = h(\mathbf{x}_t, \mathbf{v}_t) := H\mathbf{x}_t + \mathbf{v}_t, \quad \mathbf{v}_t \sim \mathcal{N}(0, V) \\ & \mathbf{z}_t \mid \mathbf{x}_t \sim \mathcal{N}(H\mathbf{x}_t, V), \quad H \in \mathbb{R}^{d_z \times d_x}, \ V \in \mathbb{R}^{d_z \times d_z} \end{split}$$

Nonlinear Kalman Filter

- A Bayes filter with the following assumptions:
 - **b** The prior pdf $p_{t|t}$ is Gaussian
 - **•** The motion model is linear in the state \mathbf{x}_t with Gaussian noise \mathbf{w}_t
 - The observation model is linear in the state \mathbf{x}_{τ} with Gaussian noise \mathbf{v}_{τ}
 - \blacktriangleright The motion noise \mathbf{w}_t and observation noise \mathbf{v}_t are independent of each other, of the state \mathbf{x}_t , and across time
 - The predicted and updated pdfs are forced to be Gaussian via approximation

$$\blacktriangleright \text{ Prior: } \mathbf{x}_t \mid \mathbf{z}_{0:t}, \mathbf{u}_{0:t-1} \sim \mathcal{N}(\boldsymbol{\mu}_{t|t}, \boldsymbol{\Sigma}_{t|t})$$

- Motion Model: $\mathbf{x}_{t+1} = f(\mathbf{x}_t, \mathbf{u}_t, \mathbf{w}_t), \quad \mathbf{w}_t \sim \mathcal{N}(0, W)$
- **• Observation Model**: $\mathbf{z}_t = h(\mathbf{x}_t, \mathbf{v}_t), \quad \mathbf{v}_t \sim \mathcal{N}(0, V)$
- Challenge: the predicted and updated pdfs are not Gaussian and can no longer be evaluated in closed form
- Moment matching: we can force the predicted and updated pdfs to be Gaussian by evaluating their first and second moments and approximating them with Gaussians with the same moments

Moment Matching

• Let $\mathbf{y} = f(\mathbf{x})$ be a nonlinear transformation of $\mathbf{x} \sim \mathcal{N}(\boldsymbol{\mu}, \boldsymbol{\Sigma})$ • The mean and (co)variance of \mathbf{y} are:

$$\begin{split} \mathbf{m} &:= \mathbb{E}[\mathbf{y}] = \int f(\mathbf{x}) \phi(\mathbf{x}; \boldsymbol{\mu}, \boldsymbol{\Sigma}) d\mathbf{x} \\ \mathcal{S} &:= \mathbb{E}\left[(\mathbf{y} - \mathbb{E}[\mathbf{y}]) (\mathbf{y} - \mathbb{E}[\mathbf{y}])^{\top} \right] = \mathbb{E}\left[\mathbf{y} \mathbf{y}^{\top} \right] - \mathbb{E}[\mathbf{y}] \mathbb{E}[\mathbf{y}]^{\top} \\ &= \int f(\mathbf{x}) f(\mathbf{x})^{\top} \phi(\mathbf{x}; \boldsymbol{\mu}, \boldsymbol{\Sigma}) d\mathbf{x} - \mathbf{m} \mathbf{m}^{\top} \end{split}$$

The covariance of **x** and **y** is:

$$\mathcal{C} := \mathbb{E}\left[\left(\mathbf{x} - oldsymbol{\mu}
ight) \left(\mathbf{y} - \mathbb{E}[\mathbf{y}]
ight)^{ op}
ight] = \int \mathbf{x} f(\mathbf{x})^{ op} \phi(\mathbf{x};oldsymbol{\mu},\Sigma) d\mathbf{x} - oldsymbol{\mu} \mathbf{m}^{ op}$$

The joint distribution of x and y can be approximated by a Gaussian:

$$\begin{pmatrix} \mathbf{x} \\ \mathbf{y} \end{pmatrix} \sim \mathcal{N} \left(\begin{pmatrix} \boldsymbol{\mu} \\ \mathbf{m} \end{pmatrix}, \begin{bmatrix} \boldsymbol{\Sigma} & \boldsymbol{C} \\ \boldsymbol{C}^\top & \boldsymbol{S} \end{bmatrix} \right)$$

The approximate distribution of x conditioned on y is:

$$\mathbf{x} \mid \mathbf{y} \sim \mathcal{N}\left(oldsymbol{\mu} + \mathcal{CS}^{-1}(\mathbf{y} - \mathbf{m}), \Sigma - \mathcal{CS}^{-1}\mathcal{C}^{ op}
ight)$$

5

Nonlinear Kalman Filter Prediction

$$\blacktriangleright \text{ Prior: } \mathsf{x}_t \mid \mathsf{z}_{0:t}, \mathsf{u}_{0:t-1} \sim \mathcal{N}(\boldsymbol{\mu}_{t|t}, \boldsymbol{\Sigma}_{t|t})$$

▶ Motion Model: $\mathbf{x}_{t+1} = f(\mathbf{x}_t, \mathbf{u}_t, \mathbf{w}_t), \quad \mathbf{w}_t \sim \mathcal{N}(0, W)$

Force a Gaussian predicted pdf via Moment Matching:

$$\mathbf{x}_{t+1} \mid \mathbf{z}_{0:t}, \mathbf{u}_{0:t} \sim \mathcal{N}(\boldsymbol{\mu}_{t+1|t}, \boldsymbol{\Sigma}_{t+1|t})$$

$$\mu_{t+1|t} = \mathbb{E} \left[\mathbf{x}_{t+1} \mid \mathbf{z}_{0:t}, \mathbf{u}_{0:t} \right]$$
$$= \int \int f(\mathbf{x}, \mathbf{u}_t, \mathbf{w}) \phi(\mathbf{x}; \boldsymbol{\mu}_{t|t}, \boldsymbol{\Sigma}_{t|t}) \phi(\mathbf{w}; 0, W) d\mathbf{x} d\mathbf{w}$$

$$\begin{split} \boldsymbol{\Sigma}_{t+1|t} &= \mathbb{E}\left[\left(\mathbf{x}_{t+1} - \boldsymbol{\mu}_{t+1|t}\right)\left(\mathbf{x}_{t+1} - \boldsymbol{\mu}_{t+1|t}\right)^{\top} \mid \mathbf{z}_{0:t}, \mathbf{u}_{0:t}\right] \\ &= \mathbb{E}\left[\mathbf{x}_{t+1}\mathbf{x}_{t+1}^{\top} \mid \mathbf{z}_{0:t}, \mathbf{u}_{0:t}\right] - \boldsymbol{\mu}_{t+1|t}\boldsymbol{\mu}_{t+1|t}^{\top} \\ &= \int \int f(\mathbf{x}, \mathbf{u}_{t}, \mathbf{w}) f(\mathbf{x}, \mathbf{u}_{t}, \mathbf{w})^{\top} \phi(\mathbf{x}; \boldsymbol{\mu}_{t|t}, \boldsymbol{\Sigma}_{t|t}) \phi(\mathbf{w}; 0, W) d\mathbf{x} d\mathbf{w} - \boldsymbol{\mu}_{t+1|t} \boldsymbol{\mu}_{t+1|t}^{\top} \end{split}$$

Nonlinear Kalman Filter Update

- $\blacktriangleright \text{ Prior: } \mathbf{x}_{t+1} \mid \mathbf{z}_{0:t}, \mathbf{u}_{0:t} \sim \mathcal{N}(\boldsymbol{\mu}_{t+1|t}, \boldsymbol{\Sigma}_{t+1|t})$
- ► Observation model: $\mathbf{z}_{t+1} = h(\mathbf{x}_{t+1}, \mathbf{v}_{t+1}), \quad \mathbf{v}_{t+1} \sim \mathcal{N}(0, V)$
- The Gaussian distribution which approximates the joint distribution of x_{t+1} and z_{t+1} conditioned on z_{0:t}, u_{0:t} via moment matching is:

$$\begin{pmatrix} \mathbf{x}_{t+1} \mid \mathbf{z}_{0:t}, \mathbf{u}_{0:t} \\ \mathbf{z}_{t+1} \mid \mathbf{z}_{0:t}, \mathbf{u}_{0:t} \end{pmatrix} \sim \mathcal{N} \left(\begin{pmatrix} \mu_{t+1|t} \\ \mathbf{m}_{t+1|t} \end{pmatrix}, \begin{bmatrix} \Sigma_{t+1|t} & C_{t+1|t} \\ C_{t+1|t}^\top & S_{t+1|t} \end{bmatrix} \right)$$
$$\mathbf{m}_{t+1|t} := \int \int h(\mathbf{x}, \mathbf{v}) \phi(\mathbf{x}; \mu_{t+1|t}, \Sigma_{t+1|t}) \phi(\mathbf{v}; 0, V) d\mathbf{x} d\mathbf{v}$$
$$S_{t+1|t} := \int \int (h(\mathbf{x}, \mathbf{v}) - \mathbf{m}_{t+1|t}) (h(\mathbf{x}, \mathbf{v}) - \mathbf{m}_{t+1|t})^\top \phi(\mathbf{x}; \mu_{t+1|t}, \Sigma_{t+1|t}) \phi(\mathbf{v}; 0, V) d\mathbf{x} d\mathbf{v}$$
$$C_{t+1|t} := \int \int (\mathbf{x} - \mu_{t+1|t}) (h(\mathbf{x}, \mathbf{v}) - \mathbf{m}_{t+1|t})^\top \phi(\mathbf{x}; \mu_{t+1|t}, \Sigma_{t+1|t}) \phi(\mathbf{v}; 0, V) d\mathbf{x} d\mathbf{v}$$

• The conditional Gaussian distribution of $\mathbf{x}_{t+1} \mid \mathbf{z}_{t+1}, \mathbf{z}_{0:t}, \mathbf{u}_{0:t}$ is then:

$$\mu_{t+1|t+1} := \mu_{t+1|t} + K_{t+1|t} (\mathbf{z}_{t+1} - \mathbf{m}_{t+1|t})$$

$$\Sigma_{t+1|t+1} := \Sigma_{t+1|t} - K_{t+1|t} S_{t+1|t} K_{t+1|t}^{\top}$$

$$K_{t+1|t} := C_{t+1|t} S_{t+1|t}^{-1}$$
7

Extended and Unscented Kalman Filters

- The EKF and UKF use different methods to approximate the five integrals required to implement a nonlinear Kalman filter
- The EKF uses a first-order Taylor series approximation to the motion and observation models around the state and noise means:

$$\begin{split} f(\mathbf{x}_t, \mathbf{u}_t, \mathbf{w}_t) &\approx f(\boldsymbol{\mu}_{t|t}, \mathbf{u}_t, \mathbf{0}) + \left[\frac{df}{d\mathbf{x}}(\boldsymbol{\mu}_{t|t}, \mathbf{u}_t, \mathbf{0})\right] (\mathbf{x}_t - \boldsymbol{\mu}_{t|t}) + \left[\frac{df}{d\mathbf{w}}(\boldsymbol{\mu}_{t|t}, \mathbf{u}_t, \mathbf{0})\right] (\mathbf{w}_t - \mathbf{0}) \\ h(\mathbf{x}_{t+1}, \mathbf{v}_{t+1}) &\approx h(\boldsymbol{\mu}_{t+1|t}, \mathbf{0}) + \left[\frac{dh}{d\mathbf{x}}(\boldsymbol{\mu}_{t+1|t}, \mathbf{0})\right] (\mathbf{x}_{t+1} - \boldsymbol{\mu}_{t+1|t}) + \left[\frac{dh}{d\mathbf{v}}(\boldsymbol{\mu}_{t+1|t}, \mathbf{0})\right] (\mathbf{v}_{t+1} - \mathbf{0}) \end{split}$$

The UKF uses a finite set of sigma points to approximate the prior Gaussian pdfs and convert the integrals to a sum. This resembles Monte Carlo approximation but the sigma points are selected deterministically.

Extended Kalman Filter Prediction

► Let
$$F_t := \frac{df}{d\mathbf{x}}(\boldsymbol{\mu}_{t|t}, \mathbf{u}_t, \mathbf{0})$$
 and $Q_t := \frac{df}{d\mathbf{w}}(\boldsymbol{\mu}_{t|t}, \mathbf{u}_t, \mathbf{0})$ so that:
 $f(\mathbf{x}_t, \mathbf{u}_t, \mathbf{w}_t) \approx f(\boldsymbol{\mu}_{t|t}, \mathbf{u}_t, \mathbf{0}) + F_t(\mathbf{x}_t - \boldsymbol{\mu}_{t|t}) + Q_t \mathbf{w}_t$

▶ Then, the predicted mean and cov can be computed in closed form:

$$\begin{split} \boldsymbol{\mu}_{t+1|t} &\approx \iint \left(f(\boldsymbol{\mu}_{t|t}, \mathbf{u}_{t}, \mathbf{0}) + F_{t}(\mathbf{x} - \boldsymbol{\mu}_{t|t}) + Q_{t}\mathbf{w} \right) \phi(\mathbf{x}; \boldsymbol{\mu}_{t|t}, \boldsymbol{\Sigma}_{t|t}) \phi(\mathbf{w}; 0, W) d\mathbf{x} d\mathbf{w} \\ &= f(\boldsymbol{\mu}_{t|t}, \mathbf{u}_{t}, \mathbf{0}) + F_{t} \left(\int \mathbf{x} \phi(\mathbf{x}; \boldsymbol{\mu}_{t|t}, \boldsymbol{\Sigma}_{t|t}) d\mathbf{x} - \boldsymbol{\mu}_{t|t} \right) + Q_{t} \int \mathbf{w} \phi(\mathbf{w}; 0, W) d\mathbf{w} \\ &= \boxed{f(\boldsymbol{\mu}_{t|t}, \mathbf{u}_{t}, \mathbf{0})} \\ \Sigma_{t+1|t} \approx \iint \left(f(\boldsymbol{\mu}_{t|t}, \mathbf{u}_{t}, \mathbf{0}) + F_{t}(\mathbf{x} - \boldsymbol{\mu}_{t|t}) + Q_{t}\mathbf{w} \right) \left(f(\boldsymbol{\mu}_{t|t}, \mathbf{u}_{t}, \mathbf{0}) + F_{t}(\mathbf{x} - \boldsymbol{\mu}_{t|t}) + Q_{t}\mathbf{w} \right)^{\top} \phi(\mathbf{x}; \boldsymbol{\mu}_{t|t}, \boldsymbol{\Sigma}_{t|t}) d\mathbf{w} d\mathbf{w} \\ &- \boldsymbol{\mu}_{t+1|t} \boldsymbol{\mu}_{t+1|t}^{\top} \\ &= f(\boldsymbol{\mu}_{t|t}, \mathbf{u}, \mathbf{0}) \left(\int (\mathbf{x} - \boldsymbol{\mu}_{t|t})^{\top} \phi(\mathbf{x}; \boldsymbol{\mu}_{t|t}, \boldsymbol{\Sigma}_{t|t}) d\mathbf{x} \right) F_{t}^{\top} + F_{t} \left(\int (\mathbf{x} - \boldsymbol{\mu}_{t|t}) \phi(\mathbf{x}; \boldsymbol{\mu}_{t|t}, \mathbf{\Sigma}_{t|t}) d\mathbf{x} \right) f(\boldsymbol{\mu}_{t|t}, \mathbf{u}_{t}, \mathbf{0})^{\top} \\ &+ F_{t} \left(\int (\mathbf{x} - \boldsymbol{\mu}_{t|t}) (\mathbf{x} - \boldsymbol{\mu}_{t|t})^{\top} \phi(\mathbf{x}; \boldsymbol{\mu}_{t|t}, \boldsymbol{\Sigma}_{t|t}) d\mathbf{x} \right) F_{t}^{\top} + Q_{t} \left(\int \mathbf{w} \mathbf{w}^{\top} \phi(\mathbf{w}; 0, W) d\mathbf{w} \right) Q_{t}^{\top} \\ &= \boxed{F_{t} \boldsymbol{\Sigma}_{t|t} F_{t}^{\top} + Q_{t} W Q_{t}^{\top}} \end{split}$$

Extended Kalman Filter Update

► Let
$$H_{t+1} := \frac{dh}{d\mathbf{x}}(\boldsymbol{\mu}_{t+1|t}, \mathbf{0})$$
 and $R_{t+1} := \frac{dh}{d\mathbf{v}}(\boldsymbol{\mu}_{t+1|t}, \mathbf{0})$ so that:
 $h(\mathbf{x}_{t+1}, \mathbf{v}_{t+1}) \approx h(\boldsymbol{\mu}_{t+1|t}, \mathbf{0}) + H_{t+1}(\mathbf{x}_{t+1} - \boldsymbol{\mu}_{t+1|t}) + R_{t+1}\mathbf{v}_{t+1}$

• The joint distribution of \mathbf{x}_{t+1} and \mathbf{z}_{t+1} can be computed in closed form:

$$\begin{split} \mathbf{m}_{t+1|t} &:= \int \int h(\mathbf{x}, \mathbf{v}) \phi(\mathbf{x}; \boldsymbol{\mu}_{t+1|t}, \boldsymbol{\Sigma}_{t+1|t}) \phi(\mathbf{v}; 0, V) d\mathbf{x} d\mathbf{v} \approx \boxed{h(\boldsymbol{\mu}_{t+1|t}, \mathbf{0})} \\ S_{t+1|t} &:= \int \int (h(\mathbf{x}, \mathbf{v}) - \mathbf{m}_{t+1|t}) (h(\mathbf{x}, \mathbf{v}) - \mathbf{m}_{t+1|t})^{\top} \phi(\mathbf{x}; \boldsymbol{\mu}_{t+1|t}, \boldsymbol{\Sigma}_{t+1|t}) \phi(\mathbf{v}; 0, V) d\mathbf{x} d\mathbf{v} \\ &\approx \boxed{H_{t+1} \boldsymbol{\Sigma}_{t+1|t} H_{t+1}^{\top} + R_{t+1} V R_{t+1}^{\top}} \\ C_{t+1|t} &:= \int \int (\mathbf{x} - \boldsymbol{\mu}_{t+1|t}) (h(\mathbf{x}, \mathbf{v}) - \mathbf{m}_{t+1|t})^{\top} \phi(\mathbf{x}; \boldsymbol{\mu}_{t+1|t}, \boldsymbol{\Sigma}_{t+1|t}) \phi(\mathbf{v}; 0, V) d\mathbf{x} d\mathbf{v} \\ &\approx \boxed{\boldsymbol{\Sigma}_{t+1|t} H_{t+1}^{\top}} \end{split}$$

► The conditional Gaussian distribution of x_{t+1} | z_{t+1} is then:

$$\mu_{t+1|t+1} := \mu_{t+1|t} + K_{t+1|t} (\mathbf{z}_{t+1} - \mathbf{m}_{t+1|t})$$

$$\Sigma_{t+1|t+1} := \Sigma_{t+1|t} - K_{t+1|t} S_{t+1|t} K_{t+1|t}^{\top}$$

$$K_{t+1|t} := C_{t+1|t} S_{t+1|t}^{-1}$$

10

Extended Kalman Filter

Prior:

Unscented Transform

The unscented transform (Julier et al., 1995, 2000) is a numerical method for approximating the joint distribution of a Gaussian random variable x ∈ ℝ^d and a nonlinear transformation f of it:

$$\mathbf{y} = f(\mathbf{x}), \qquad \begin{pmatrix} \mathbf{x} \\ \mathbf{y} \end{pmatrix} \sim \mathcal{N}\left(\begin{pmatrix} \boldsymbol{\mu} \\ \mathbf{m} \end{pmatrix}, \begin{bmatrix} \boldsymbol{\Sigma} & \boldsymbol{C} \\ \boldsymbol{C}^{\top} & \boldsymbol{S} \end{bmatrix} \right)$$

Choose a set of 2d + 1 sigma points using the *i*-th columns of the square root √Σ of the covariance Σ = √Σ√Σ^T:

$$\mathbf{x}^{(0)} = \boldsymbol{\mu}, \qquad \mathbf{x}^{(i)} = \boldsymbol{\mu} \pm \alpha \sqrt{d+k} \left[\sqrt{\Sigma} \right]_i, \quad i = 1, \dots, d$$

• $\sqrt{\Sigma}$ is lower-triangular and can be obtained via **Cholesky factorization**

▶ $\alpha \in (0,1]$ and k > -d determine the sigma points spread

The sigma points capture the shape of the original distribution of x

Unscented Transform

- Each sigma point x⁽ⁱ⁾ is associated with a mean weight v⁽ⁱ⁾ and a covariance weight w⁽ⁱ⁾
 - Choose $v^{(0)} = 1 \frac{d}{\alpha^2(d+k)} < 1$ and $w^{(0)} \ge v^{(0)}$

• Let
$$v^{(i)} = w^{(i)} = \frac{1 - v^{(0)}}{2d}$$
 for $i = 1, \dots, 2d$

• Let
$$\mathbf{x}^{(0)} = \boldsymbol{\mu}$$
 and $\mathbf{x}^{(i)} = \boldsymbol{\mu} \pm \sqrt{\frac{d}{1 - \mathbf{v}^{(0)}}} \left[\sqrt{\Sigma} \right]_i$ for $i = 1, \dots, d$

The weighted sigma points are used to approximate the integrals that determine the mean and covariance of y = f(x):

$$\mathbb{E}[\mathbf{y}] \approx \mathbf{m} = \sum_{i=0}^{2d} v^{(i)} f(\mathbf{x}^{(i)})$$
$$Cov[\mathbf{y}, \mathbf{y}] \approx S = \sum_{i=0}^{2d} w^{(i)} \left(f(\mathbf{x}^{(i)}) - \mathbf{m} \right) \left(f(\mathbf{x}^{(i)}) - \mathbf{m} \right)^{\top}$$
$$Cov[\mathbf{x}, \mathbf{y}] \approx C = \sum_{i=0}^{2d} w^{(i)} \left(\mathbf{x}^{(i)} - \mu \right) \left(f(\mathbf{x}^{(i)}) - \mathbf{m} \right)^{\top}$$

Unscented Kalman Filter Prediction

- $\blacktriangleright \text{ Prior: } \mathsf{x}_t \mid \mathsf{z}_{0:t}, \mathsf{u}_{0:t-1} \sim \mathcal{N}(\boldsymbol{\mu}_{t|t}, \boldsymbol{\Sigma}_{t|t})$
- ▶ Motion Model: $\mathbf{x}_{t+1} = f(\mathbf{x}_t, \mathbf{u}_t, \mathbf{w}_t), \quad \mathbf{w}_t \sim \mathcal{N}(0, W)$
- Sigma Point Weights:

$$v^{(0)} < 1$$
 $w^{(0)} \ge v^{(0)}$ $v^{(i)} = w^{(i)} = rac{1 - v^{(0)}}{2(d_x + d_w)}$ $i = 1, \dots, 2(d_x + d_w)$

Sigma Points:

$$\begin{pmatrix} \mathbf{x}_{t|t}^{(0)} \\ \mathbf{w}^{(0)} \end{pmatrix} = \begin{pmatrix} \boldsymbol{\mu}_{t|t} \\ \mathbf{0} \end{pmatrix}, \qquad \begin{pmatrix} \mathbf{x}_{t|t}^{(i)} \\ \mathbf{w}^{(i)} \end{pmatrix} = \begin{pmatrix} \boldsymbol{\mu}_{t|t} \\ \mathbf{0} \end{pmatrix} \pm \sqrt{\frac{(d_x + d_w)}{1 - v^{(0)}}} \begin{bmatrix} \sqrt{\Sigma_{t|t}} & \mathbf{0} \\ \mathbf{0} & \sqrt{W} \end{bmatrix}_i$$

Prediction:

$$\mu_{t+1|t} = \sum_{i=0}^{2(d_x+d_w)} v^{(i)} f\left(\mathbf{x}_{t|t}^{(i)}, \mathbf{u}_t, \mathbf{w}^{(i)}\right)$$

$$\Sigma_{t+1|t} = \sum_{i=0}^{2(d_x+d_w)} w^{(i)} \left(f\left(\mathbf{x}_{t|t}^{(i)}, \mathbf{u}_t, \mathbf{w}^{(i)}\right) - \mu_{t+1|t} \right) \left(f\left(\mathbf{x}_{t|t}^{(i)}, \mathbf{u}_t, \mathbf{w}^{(i)}\right) - \mu_{t+1|t} \right)^\top$$

Unscented Kalman Filter Update

Prior: x_{t+1} | z_{0:t}, u_{0:t} ~ N(μ_{t+1|t}, Σ_{t+1|t})
 Observation Model: z_{t+1} = h(x_{t+1}, v_{t+1}), v_{t+1} ~ N(0, V)
 Sigma Points:

• Kalman Gain: $K_{t+1|t} = C_{t+1|t} S_{t+1|t}^{-1}$

$$\mathbf{m}_{t+1|t} = \sum_{i=0}^{2(d_{x}+d_{v})} v^{(i)} h\left(\mathbf{x}_{t+1|t}^{(i)}, \mathbf{v}^{(i)}\right)$$

$$S_{t+1|t} = \sum_{i=0}^{2(d_{x}+d_{v})} w^{(i)} \left(h\left(\mathbf{x}_{t+1|t}^{(i)}, \mathbf{v}^{(i)}\right) - \mathbf{m}_{t+1|t}\right) \left(h\left(\mathbf{x}_{t+1|t}^{(i)}, \mathbf{v}^{(i)}\right) - \mathbf{m}_{t+1|t}\right)^{\top}$$

$$C_{t+1|t} = \sum_{i=0}^{2(d_{x}+d_{v})} w^{(i)} \left(\mathbf{x}_{t+1|t}^{(i)} - \boldsymbol{\mu}_{t+1|t}\right) \left(h\left(\mathbf{x}_{t+1|t}^{(i)}, \mathbf{v}^{(i)}\right) - \mathbf{m}_{t+1|t}\right)^{\top}$$
15

Unscented Kalman Filter (additive noise) $\mathbf{x}_{t+1} \mid \mathbf{z}_{0:t}, \mathbf{u}_{0:t} \sim \mathcal{N}(\boldsymbol{\mu}_{t+1|t}, \boldsymbol{\Sigma}_{t+1|t})$ Prior Motion model $\mathbf{x}_{t+1} = f(\mathbf{x}_t, \mathbf{u}_t) + \mathbf{w}_t, \quad \mathbf{w}_t \sim \mathcal{N}(0, W)$ $\mathbf{z}_{t+1} = h(\mathbf{x}_{t+1}) + \mathbf{v}_{t+1}, \quad \mathbf{v}_{t+1} \sim \mathcal{N}(0, V)$ Obs. model $\mu_{t+1|t} = \sum_{i=0}^{-\infty} v^{(i)} f\left(\mathbf{x}_{t|t}^{(i)}, \mathbf{u}_{t}\right), \quad \mathbf{x}_{t|t}^{(0)} = \mu_{t|t}, \quad \mathbf{x}_{t|t}^{(i)} = \mu_{t|t} \pm \sqrt{\frac{d_{x}}{1 - v^{(0)}}} \left[\sqrt{\Sigma_{t|t}}\right]_{i}$ Predict $\Sigma_{t+1|t} = \sum_{i=1}^{20_x} w^{(i)} \left(f\left(\mathbf{x}_{t|t}^{(i)}, \mathbf{u}_t\right) - \boldsymbol{\mu}_{t+1|t} \right) \left(f\left(\mathbf{x}_{t|t}^{(i)}, \mathbf{u}_t\right) - \boldsymbol{\mu}_{t+1|t} \right)^\top + W$ $\mu_{t+1|t+1} = \mu_{t+1|t} + K_{t+1|t} (\mathbf{z}_{t+1} - \mathbf{m}_{t+1|t})$ Update $\Sigma_{t+1|t+1} = \Sigma_{t+1|t} - K_{t+1|t} S_{t+1|t} K_{t+1|t}^{\dagger}$ Kalman gain $K_{t+1|t} = C_{t+1|t} S_{t+1|t}^{-1}$ $\mathbf{m}_{t+1|t} = \sum_{i=1}^{N} v^{(i)} h\left(\mathbf{x}_{t+1|t}^{(i)}\right), \qquad \mathbf{x}_{t+1|t}^{(0)} = \mu_{t+1|t}, \quad \mathbf{x}_{t+1|t}^{(i)} = \mu_{t+1|t} \pm \sqrt{\frac{d_x}{1 - v^{(0)}}} \left[\sqrt{\Sigma_{t+1|t}}\right]_i$ $S_{t+1|t} = \sum_{i=0}^{2\omega_x} w^{(i)} \left(h\left(\mathbf{x}_{t+1|t}^{(i)} \right) - \mathbf{m}_{t+1|t} \right) \left(h\left(\mathbf{x}_{t+1|t}^{(i)} \right) - \mathbf{m}_{t+1|t} \right)^\top + V$ $C_{t+1|t} = \sum_{i=1}^{20x} w^{(i)} \left(\mathbf{x}_{t+1|t}^{(i)} - \mu_{t+1|t} \right) \left(h \left(\mathbf{x}_{t+1|t}^{(i)} \right) - \mathbf{m}_{t+1|t} \right)^{\top}$



Applying a nonlinear transformation to the random variable on the left results in a new random variable (right)

EKF: Linearization-based approximation to the transformation formed by calculating the curvature at the mean (solid) and true covariance (dashed).

UKF: Unscented transform approximation to the transformation formed by propagating sigma points through the nonlinearity and estimating the covariance from them (solid) and true covariance (dashed).

Noisy Pendulum Tracking

- Consider a simple pendulum consisting of a mass m hanging from a string of length L and fixed at a pivot point P
- The differential equation for the pendulum motion can be obtained using Newton's second law for rotational systems which relates the net external torque τ (position × force) to the product of the moment of inertia I = mL² and the angular acceleration θ(t):



$$\tau = -mgL\sin\theta(t) = mL^2\ddot{\theta}(t) \quad \Rightarrow \quad \ddot{\theta}(t) = -\frac{g}{L}\sin\theta(t) + \underbrace{w(t)}_{\text{noise}\sim\mathcal{N}(0,q)}$$

► The model can be converted into a state-space model with state $\mathbf{x}(t) := (\theta(t), \omega(t))^{\top}$, where $\omega(t) := \dot{\theta}(t)$ as follows: $\frac{d}{dt} \begin{pmatrix} \theta(t) \\ \omega(t) \end{pmatrix} = \begin{bmatrix} \omega(t) \\ -\frac{g}{L} \sin(\theta(t)) \end{bmatrix} + \begin{bmatrix} 0 \\ 1 \end{bmatrix} w(t)$

Discrete-time Model

Motion model: a simple discretization of the pendulum state-space model with sampling period τ leads to:

$$\mathbf{x}_{t+1} = \begin{pmatrix} \theta_{t+1} \\ \omega_{t+1} \end{pmatrix} = \underbrace{\begin{bmatrix} \theta_t + \tau \omega_t \\ \omega_t - \tau \frac{g}{L} \sin \theta_t \end{bmatrix}}_{f(\mathbf{x}_t, \mathbf{w}_t)} + \mathbf{w}_t, \quad \mathbf{w}_t \sim \mathcal{N}\left(\mathbf{0}, \underbrace{q \begin{bmatrix} \frac{\tau^3}{3} & \frac{\tau^2}{2} \\ \frac{\tau^2}{2} & \tau \end{bmatrix}}_{W}\right)$$

Observation model: consider estimating the angle θ_t and the velocity ω_t of the pendulum using measurements of its deviation from rest position, i.e.,:

$$z_t = \underbrace{L\sin(\theta_t) + v_t}_{h(\mathbf{x}_t, v_t)}, \qquad v_t \sim \mathcal{N}(0, V)$$

Extended Kalman Filter

► Prior:
$$\mathbf{x}_t \mid \mathbf{z}_{0:t} \sim \mathcal{N}(\boldsymbol{\mu}_{t|t}, \boldsymbol{\Sigma}_{t|t})$$
 with $\boldsymbol{\mu}_{t|t} = \begin{bmatrix} \mu_{t|t}^{\theta} \\ \mu_{t|t}^{\omega} \end{bmatrix}$

Motion Model Jacobian:

$$F_t := \begin{bmatrix} 1 & \tau \\ -\tau \frac{g}{L} \cos \mu_{t|t}^{\theta} & 1 \end{bmatrix} \qquad \qquad Q_t := I$$

Prediction:

$$\boldsymbol{\mu}_{t+1|t} = f(\boldsymbol{\mu}_{t|t}, \boldsymbol{0}) = \begin{bmatrix} \mu_{t|t}^{\theta} + \tau \mu_{t|t}^{\omega} \\ \mu_{t|t}^{\omega} - \tau \frac{g}{L} \sin \mu_{t|t}^{\theta} \end{bmatrix}$$
$$\boldsymbol{\Sigma}_{t+1|t} = F_t \boldsymbol{\Sigma}_{t|t} F_t^{\top} + Q_t W Q_t^{\top}$$

Extended Kalman Filter

• Prediction:
$$\mathbf{x}_{t+1} \mid \mathbf{z}_{0:t} \sim \mathcal{N}(\boldsymbol{\mu}_{t+1|t}, \boldsymbol{\Sigma}_{t+1|t})$$
 with $\boldsymbol{\mu}_{t+1|t} = \begin{bmatrix} \mu_{t+1|t}^{\theta} \\ \mu_{t+1|t}^{\omega} \end{bmatrix}$

Observation Model Jacobian:

$$H_{t+1} := \begin{bmatrix} L \cos \mu_{t+1|t}^{\theta} & 0 \end{bmatrix} \qquad \qquad R_{t+1} := I$$

- ► Innovation: $r_{t+1|t} := z_{t+1} L \sin(\mu_{t+1|t}^{\theta})$
- Measurement/innovation covariance: $S_{t+1|t} := H_{t+1} \Sigma_{t+1|t} H_{t+1}^{\top} + V$
- State-measurement cross-covariance: $\Sigma_{t+1|t} H_{t+1}^{\top}$
- Kalman gain: $K_{t+1|t} = \Sigma_{t+1|t} H_{t+1}^{\top} S_{t+1|t}^{-1}$

• Update:
$$\mu_{t+1|t+1} = \mu_{t+1|t} + K_{t+1|t}r_{t+1|t}$$

 $\Sigma_{t+1|t+1} = \Sigma_{t+1|t} - K_{t+1|t}H_{t+1}\Sigma_{t+1|t}$

EKF Performance

▶ $\tau = 0.001$, q = 0.3, g = 9.81, L = 1, V = 0.64

Prediction at 1000 Hz, update at 20 Hz



Uscented Kalman Filter Prediction

• Prior:
$$\mathbf{x}_t \mid z_{0:t} \sim \mathcal{N}(\boldsymbol{\mu}_{t|t}, \boldsymbol{\Sigma}_{t|t})$$

Sigma points:

$$\mathbf{v}^{(0)} < 1 \qquad \mathbf{w}^{(0)} \ge \mathbf{v}^{(0)} \qquad \mathbf{v}^{(i)} = \mathbf{w}^{(i)} = \frac{1 - \mathbf{v}^{(0)}}{2d_{\mathsf{X}}}, \quad i = 1, \dots, 2d_{\mathsf{X}}$$
$$\mathbf{x}^{(0)}_{t|t} = \boldsymbol{\mu}_{t|t}, \qquad \mathbf{x}^{(i)}_{t|t} = \boldsymbol{\mu}_{t|t} \pm \sqrt{\frac{d_{\mathsf{X}}}{1 - \mathbf{v}^{(0)}}} \left[\sqrt{\boldsymbol{\Sigma}_{t|t}} \right]_{i}, \quad i = 1, \dots, 2d_{\mathsf{X}}$$

Prediction:
$$\mu_{t+1|t} = \sum_{i=0}^{2d_x} v^{(i)} f(\mathbf{x}_{t|t}^{(i)}, \mathbf{0})$$

$$\Sigma_{t+1|t} = \sum_{i=0}^{2d_x} w^{(i)} \left(f(\mathbf{x}_{t|t}^{(i)}, \mathbf{0}) - \mu_{t+1|t} \right) \left(f(\mathbf{x}_{t|t}^{(i)}, \mathbf{0}) - \mu_{t+1|t} \right)^\top + W$$

Uscented Kalman Filter Update

Sigma points:

$$\mathbf{x}_{t+1|t}^{(0)} = \boldsymbol{\mu}_{t+1|t}, \qquad \mathbf{x}_{t+1|t}^{(i)} = \boldsymbol{\mu}_{t+1|t} \pm \sqrt{\frac{d_x}{1-v^{(0)}}} \left[\sqrt{\Sigma_{t+1|t}}\right]_i, \quad i = 1, \dots, 2d_x$$

• Expected measurement: $m_{t+1|t} = \sum_{i=0}^{2G_x} v^{(i)} h\left(\mathbf{x}_{t+1|t}^{(i)}, 0\right)$

• Innovation:
$$r_{t+1|t} := z_{t+1} - m_{t+1|t}$$

Measurement/innovation covariance:

$$S_{t+1|t} = \sum_{i=0}^{2d_x} w^{(i)} \left(h\left(\mathbf{x}_{t+1|t}^{(i)}, 0 \right) - m_{t+1|t} \right) \left(h\left(\mathbf{x}_{t+1|t}^{(i)}, 0 \right) - m_{t+1|t} \right)^\top + V$$

State-measurement cross-covariance: $C_{t+1|t} = \sum_{i=0}^{2d_x} w^{(i)} \left(\mathbf{x}_{t+1|t}^{(i)} - \boldsymbol{\mu}_{t+1|t} \right) \left(h \left(\mathbf{x}_{t+1|t}^{(i)}, 0 \right) - m_{t+1|t} \right)^{\top}$

Kalman gain: $K_{t+1|t} = C_{t+1|t}S_{t+1|t}^{-1}$ Update: $\frac{\mu_{t+1|t+1} = \mu_{t+1|t} + K_{t+1|t}r_{t+1|t}}{\Sigma_{t+1|t+1} = \Sigma_{t+1|t} - K_{t+1|t}S_{t+1|t}K_{t+1|t}^{\top}}$

UKF Performance

▶ $\tau = 0.001$, q = 0.3, g = 9.81, L = 1, V = 0.64

Prediction at 1000 Hz, update at 20 Hz



UKF vs EKF Predicted Covariance

 $\blacktriangleright \text{ Prior: } \mathcal{N}\left(\begin{pmatrix} \frac{\pi}{4} \\ -1 \end{pmatrix}, \begin{bmatrix} 2 & -0.3 \\ -0.3 & 0.5 \end{bmatrix}\right)$

• One prediction step with parameters $\tau = 1$, g = 9.81, L = 1





